Cbox DMX O3 2x100W

Fully Assembled Control+Power Box Dual Circuit, 2x100W, 24VDC, CV, DMX512 Enabled



The Cbox are completely integrated, highly-customizable, fully cULus Listed Class 2 power and control boxes rated for Dry and Wet Locations. All Cbox enclosures arrive to site assembled and ready for quick wiring and install. All required components included. The DMX O3 are configurable DMX512 enabled power boxes. Integrate up to 200W through multiple Class 2 circuits.



CLIENT	
PROJECT NAME	
LOCATION	
DATE	

Product Detail






	Input Voltage	120-277VAC			
	Input Frequency	50-60 Hz			
		0.93A			
	Max Input Current				
	Output Voltage	24VDC, Constant Voltage			
	Power	2 x 100W			
	Min. Power Draw	2 x 10W			
	Control	DMX512			
	Max. Output Current	4.1A			
Electrical		Screw Terminals			
	Connections	3 Pins XLR terminal			
		2xRJ45 Terminal			
	Start-up Time	<1000ms			
	Protection	Cat. C3 Surge Location (10kA/10kV)			
	Surge Current Rating	20,000A, 8/20 µSec Wave			
	Rating (2mS)	540 Joules			
	Max. Clamping Voltage	925V			
	Ambient Temperature	-4°F to 122°F (-20°C to 50°C)			
	Circuit	Class 2			
	Average Life	50,000 hours			
	Housing Construction	PVC (enclosure)			
Mechanical	Weight	13.5lbs (6.12kg)			
	Environmental	IP66			

Ordering								
Product Code	Series	Power	Output	Input Voltage	IP Rating			
СВДМХОЗ	Р	2x100W	24		IP66			

Dimensions



BL LIGHTING

III - 8838 Heather St. Vancouver, BC. Canada. V6P 3S8 P: 1-604-874-4405 E: info@bllighting.com Copyright © BL INNOVATIVE LIGHTING. All Rights Reserved. Solid State Lighting is sensitive to power fluctuations. Surge protection is highly recommended for all LED lighting products and should be on a dedicated circuit to protect against premature failure. Lack of surge protection may void your warranty. Designed & Assembled in North America.

Specifications subject to change without notice. Please refer to our website at bllighting.com for current technical data.

com bllighting.com

For more information,

please download the BL LIGHTING catalog

1